

IS-G300

WiFi and GSM (3G/4G)
Smart Alarm System Kit



iSecus IS-G300 is a full featured wireless smart alarm system kit that supports WiFi, 3G/4G. It can place calls and send text notification through a Sim card or WiFi.

The alarm hub adopts 2.4TFT touch screen with a user-friendly interface to quickly and easily configure the system. It can support 99 wireless alarm zones, 3 wired alarm zones, 10 RFID tags and 10 remote tags. This allows you to have a wide range of monitoring on your home, office or factory.

By default, Tuya app (Android & iOS) is recommended which can realize linkage function with other Tuya smart home items. Besides, IS-G300 is also compatible with Google Assistant and Amazon Alexa to realize voice control.

Specifications

Hub (1pc)

Power Supply: Micro USB 110/220VAC to 5V, 1000mA

Backup Battery: 3.7V, 500mAh Rechargeable Lithium Battery

Consumption: <55mA@normal

Siren Output: <500mA

Radio Frequency: 433Mhz

GSM: 850/900/1800/1900MHz

Wi-Fi: IEEE802.11b/g/n

Operation Temperature: -10~55°C

Remote Controller (2pcs)

Power Supply: DC 3V (CR2025 Lithium Battery x1)

Standby Current: <5uA

Alarm Current: <15mA

Transmitting Distance: <80m (Open Area and No Interference)

Radio Frequency: 433Mhz

Operation Temperature: -10~55°C

Door/Window Sensor (1pc)

Power Supply: DC 3V (CR2032 Lithium Battery x1)

Standby Current: <8uA

Alarm Current: <15mA

Transmitting Distance: <80m (Open Area/No Interference)

Radio Frequency: 433Mhz

Operation Temperature: -10~55°C

PIR Motion Sensor (1pc)

Power Supply: 1.5V AA Battery x3

Standby Current: <15uA

Alarm Current: <25mA

Detection Scope: <12m/110°

Transmitting Distance: <80m (Open Area and No Interference)

Radio Frequency: 433Mhz

Operation Temperature: -10~55°C

RFID Tag (2pcs)

Chip: 4100/4200

Frequency: 125KHz

Read Distance: <2cm

Wireless Siren (1pc)

Power Supply: Micro USB 110/220VAC to 5V, 1000mA

Backup Battery: 3.7V, 300mAh Rechargeable Lithium Battery

Standby Current: <15mA

Alarm Current: <230mA

Volume: 100dB

Radio Frequency: 433Mhz

Operation Temperature: -10~55°C

Available App:



Smart Life

Scan the above QR code or find "TuyaSmart" in Apple Store or Google Play to get free App.